

# BATTERY-OPERATED POWER SUPPLY

Inventor: Erlend Olson

## CROSS-REFERENCE TO RELATED APPLICATIONS

- [0001] This application claims priority to the following provisional application, which is incorporated by reference in its entirety herein: U.S. Patent Application Serial No. 60/264,259, entitled "Battery-Operated Power Supply," filed January 29, 2001, by Olson (still pending).

## BACKGROUND OF THE INVENTION

### Field of the Invention

- [0002] The present invention relates to a system and method for operating a power supply. More specifically, the present invention relates to a system and method for utilizing battery power sources in an electronic power supply.

### Background

- [0003] Conventional electronic power supplies that operate using battery power sources suffer from a number of disadvantages.
- [0004] For example, a conventional method for providing a DC voltage to a DC-DC converter utilizes two or more batteries in a series configuration. Often, when batteries are configured serially, one battery will become depleted well in advance of the others. This is due, in part, to varying internal series resistances as well as other characteristics that may cause each battery to discharge at a different rate. Where one battery dies in advance of the others in a series configuration, no power can be delivered to the device being powered.
- [0005] Recharging batteries that are in series can also be problematic. Because the batteries in a stack typically discharge at different rates, the voltage in each

battery before recharging will be different. If one of the batteries in series has been severely discharged to the point where gas has started to build on the anode or cathode, that battery can actually reverse polarity. When an attempt is made to recharge the batteries, the battery with a reverse polarity will, in effect, be charged in reverse. This will result in the death of that battery, which means that no power can be delivered to the device being powered as discussed above. Additionally, it has been observed that charging a battery with a reverse polarity can actually cause the battery to be damaged or heat up to the point where it will explode.

[0006] Furthermore, when batteries are arranged in series, it is difficult to monitor how much charge is in each of them. Because batteries are manufactured with slight differences, each individual battery will charge and discharge at a different rate. It would be useful to know for discharging and recharging purposes how much charge remains in each battery in a battery pack. In a conventional series arrangement, the overall voltage coming out of a battery pack may be detected, but it is impossible to determine the state of one of the cells in the middle of the stack.

[0007] Conventional schemes for operating two or more battery cells in parallel are also disadvantageous in that they require the addition of external parts to add multiple cells to a battery pack, which can be complex and costly. Moreover, conventional techniques for operating cells in parallel do not avoid the problem of over-discharging, or "deep" discharging of a battery that can result in polarity reversal.

[0008] A further disadvantage of conventional battery-operated power supplies is that they utilize separate power control chips that must be coupled to the application to be powered using external logic and parts. This makes the design more expensive. Furthermore, because these separate power control chips are not "on chip" with the application being powered, they do not have access to *a priori* information about impending load changes. Thus, conventional battery-operated power supplies require large load capacitors to act as charge buffers to prevent

sudden load changes from pulling a supply voltage out of specification (in the case where a large load is suddenly presented) or from causing the supply voltage to spike too high (in the case where the load current is suddenly turned off).

[0009] Conventional battery-operated power supplies also do not monitor the state of batteries by determining how much charge is in them, but instead simply look at the voltage on the battery. Although the voltage on the battery provides an indication of the state of the battery, that information is not as useful as tracking how much charge remains in the battery.

[0010] Conventional battery-operated power supplies are also disadvantageous in that they typically utilize a Schottky diode to discharge current into a load. Because a Schottky diode has a typical turn-on voltage of about 0.4 to 0.6 volts, the use of the diode will result in an energy loss equal to the turn-on voltage times the load current. This is lost energy that could have otherwise been used by the load. Where only one or two small batteries are being used, this loss can be quite significant. The use of Schottky diodes is also problematic because it is impossible to control their turn-on and turn-off characteristics beyond their manufactured values.

#### BRIEF SUMMARY OF THE INVENTION

[0011] There is a great need for innovative techniques that would enable portable electronic equipment to operate more efficiently from battery power sources. For example, in the Bluetooth™ area of wireless products, it is anticipated that there will be great demand for Bluetooth™-compatible headsets. High efficiency and small size are essential to the success of any Bluetooth™ headset. A battery-operated power supply is used to power the headset at the correct voltage from rechargeable batteries.

[0012] The present invention provides a system and method for drawing charge from two or more batteries under the control of a power controller, wherein the power controller may control and monitor the amount and rate of discharge. The

present invention may also be used to recharge two or more batteries under the control of a power controller, wherein the power controller may control and monitor the amount and rate of charging. In an embodiment, the present invention may be used to provide power to a DC to DC converter and to recharge batteries used for providing power to a DC to DC converter.

[0013] The present invention is advantageous in that it provides a separate connection to each battery for charging and recharging purposes. As a result, the depletion of any single cell in a battery pack will not result in a complete loss of power to the application being powered, as charge may be drawn from any of the other cells that have not yet been depleted. In fact, the power controller of the present invention may be used to increase the power drawn from the surviving cells to compensate for the loss of the depleted battery.

[0014] Because embodiments of the present invention provide a separate connection to each battery, the state of each battery may be monitored on an individual basis. As a result, each cell can be charged and discharged in an optimal way. For example, polarity reversal may be avoided by tracking the amount of charge that has been drawn off of each battery in the battery pack. Additionally, discharging and recharging may be evenly applied to each cell. Optimal charging and discharging of each battery will permit the battery to last through more charge/discharge cycles, hold more power before needing charging, and be far more reliable than batteries in conventional power supplies.

[0015] Also, because each battery may be monitored on an individual basis, embodiments of the present invention also permit information to be provided to the user about the state of each battery, such as a warning when a battery's charge is low or when a battery is depleted.

[0016] In an embodiment of the present invention, the state of each battery is monitored by utilizing counters that maintain a continuous running total of how long the battery has been charged or discharged. This information, in turn, may be used to determine the precise amount of charge remaining in each battery. This technique represents an improvement over conventional power supply circuits, in

which the status of a battery or batteries is determined simply by looking at the voltage of a battery or batteries.

[0017] The present invention is also advantageous in that it permits the addition of multiple cells in a battery pack with a very minimal external parts count, while still keeping the cells separate so that charging can be optimized and so that the depletion of individual cells dying in the battery pack will not cause a loss of power to the entire product. As a result, embodiments of the present invention may be implemented in an easy and inexpensive manner.

[0018] Another benefit of the present invention is that it may be implemented very efficiently on-chip along with an application circuit being powered. For example, an embodiment of the present invention is implemented on-chip with an application circuit in CMOS. Since an embodiment of the present invention may be implemented in digital CMOS, digital logic may be easily added to the power controller that will allow fine tuning of the rate of charge/discharge of a given battery in light of battery condition and load demands.

[0019] Also, since embodiments of the present invention may be implemented on-chip with the application circuit being powered, the application circuit can provide useful information to the power controller to help control the power supply. For example, the application circuit can provide the power controller with *a priori* information about an impending load change. This may occur, for instance, where the application circuit is going from a standby state to an active state, or vice-versa. The access to information regarding impending load changes permits the power controller to control the power supply to increase or decrease the power supply accordingly in advance of the change. As a result, embodiments of the present invention do not require the large load capacitors of conventional designs that act as charge buffers which compensate for large and sudden load changes..

[0020] Additionally, embodiments of the present invention use a controlled FET to discharge current into a load, and thus avoid the energy loss associated with conventional designs that use a Schottky diode to perform that function. This is due to the fact that a FET may have a drain-to-source voltage that is significantly

lower than the turn-on voltage of a Schottky diode. For example, a FET with a drain-to-source voltage of 10 mV may be used as compared to a Schottky diode with a typical turn-on voltage of 0.4 to 0.6 V. Furthermore, the use of a FET in embodiments of the present invention permits precise control of turn-off and turn-on voltages as opposed to Schottky diodes, in which the turn-on and turn-off voltages cannot be modified after manufacture.

[0021] Additional features and advantages of the invention will be set forth in the description that follows, and in part will be apparent from the description, or may be learned by practice of the invention. The objectives and other advantages of the invention will be realized and attained by the system and method particularly pointed out in the written description and claims hereof as well as the appended drawings.

#### BRIEF DESCRIPTION OF THE DRAWINGS/FIGURES

[0022] The accompanying drawings, which are incorporated herein and form a part of the specification, illustrate the present invention and, together with the description, further serve to explain the principles of the invention and to enable a person skilled in the pertinent art to make and use the invention.

[0023] FIG. 1 is a functional block diagram of a battery-operated power supply in accordance with an embodiment of the present invention.

[0024] FIG. 2 is a high-level schematic of a battery-operated power supply circuit in accordance with embodiments of the present invention.

[0025] FIG. 3 is a functional block diagram of a power control circuit used in a battery-operated power supply in accordance with an embodiment of the present invention.

[0026] FIG. 4 depicts exemplary voltages and charge values for components of a battery-operated power supply circuit in accordance with an embodiment of the present invention.

[0027] The present invention will now be described with reference to the accompanying drawings. In the drawings, like reference numbers indicate identical or functionally similar elements. Additionally, the left-most digit(s) of a reference number identifies the drawing in which the reference number first appears.

## DETAILED DESCRIPTION OF THE INVENTION

[0028] FIG. 1 depicts a functional block diagram of a battery-operated power supply 100 in accordance with an embodiment of the present invention. Power supply 100 includes a first battery 101 (designated " $B_1$ "), a first inductor 102 (designated " $L_1$ "), a second battery 104 (designated " $B_2$ "), a second inductor 105 (designated " $L_2$ "), a load 107, a power controller 108, a first controlled power switch 103, a second controlled power switch 106, and an optional external power supply 109. In embodiments, the power supply 100 generates the necessary power to operate a connected application device or circuit, which is represented schematically as load 107. In other words, the power supply 100 is designed to make sure that the battery voltage provided by the first and second batteries 101 and 104 is matched to the voltage of the circuit in which those batteries are employed.

[0029] Each battery 101 and 104 is separately coupled to the load 107 via the first and second controlled power switches 103 and 106, respectively. When the first controlled power switch 103 is open, charge from the first battery 101 accumulates on the first inductor 102, and when the first controlled power switch 103 is closed, charge is delivered from the first battery 101 to the load 107. In a like fashion, when the second controlled power switch 106 is open, charge from the second battery 104 accumulates on the second inductor 104, and when the second controlled power switch 106 is closed, charge is delivered from the second battery 104 to the load 107.

[0030] The opening and closing of the controlled power switches is selectively controlled by the power controller 108. The power controller 108 is responsible for maintaining the necessary operating voltage across load 107. To do so, the power controller 108 determines what the actual voltage is across the load 107, to which it is connected. If the voltage across the load 107 is less than the voltage necessary for powering the application device or circuit, the power controller 108 operates to increase the charge delivered from the first battery 101 and/or the second battery 104. If the voltage across the load 107 is more than required for powering the application device or circuit, the power controller 108 operates to decrease the charge delivered from the first battery 101 and/or the second battery 104.

[0031] The power controller 108 increases the charge delivered from the first battery 101 by increasing the amount of time that the first controlled power switch 103 is closed and decreases the charge delivered from the first battery 101 by increasing the amount of time that the first controlled power switch 103 is open. Similarly, the power controller 108 increases the charge delivered from the second battery 104 by increasing the amount of time that the second controlled power switch 106 is closed and decreases the charge delivered from the second battery 104 by increasing the amount of time that the second controlled power switch 106 is open.

[0032] In embodiments, the controlled power switches 103 and 106 may be open and closed in an alternating fashion by the power controller 108, so that charge is delivered from only one battery at a time. Alternately, the controlled power switches 103 and 106 may be closed at the same time, so that power is delivered from both batteries at once. In further embodiments, the power controller 108 may control the controlled power switches 103 and 106 to discharge in an alternating fashion as well as simultaneously.

[0033] The design depicted in FIG. 1 is advantageous in that it provides a separate connection between each battery 101 and 104 to the load 107 for discharging purposes. As a result, the depletion of either battery 101 and 104, in and of itself,



will not result in a complete loss of power to the application device or circuit being powered, as represented by the load 107. In embodiments, the power controller 108 increases the discharge rate from the surviving battery to compensate for the loss of the depleted battery.

[0034] Furthermore, because the design depicted in FIG. 1 provides a separate connection between each battery 101 and 104 and the load 107, the state of each battery 101 and 104 can be monitored on an individual basis. For example, polarity reversal may be avoided by tracking the amount of charge that has been drawn off of the first battery 101 and the second battery 102. Additionally, the power controller 108 can operate to ensure that discharging occurs evenly as between battery 101 and 104.

[0035] The design shown in FIG. 1 can also be utilized to implement a recharging technique for the power supply 100. As shown in FIG. 1, the power supply 108 also includes an optional external power supply 109 which may be used to recharge the first battery 101 and the second battery 104. In an embodiment, charge from the external power supply 109 may be selectively applied to each battery 101 and 104 via operation of the controlled power switches 103 and 106, respectively. In such an embodiment, when the first controlled power switch 103 is open, no charge from the external power supply 109 will be supplied to the first battery 101, and when the first controlled power switch 103 is closed, charge from the external power supply 109 is delivered to the first battery 101. In a like fashion, when the second controlled power switch 106 is open, no charge from the external power supply will be supplied to the second battery 104, and when the second controlled power switch 106 is closed, charge from the external power supply 109 will be delivered to the second battery 104.

[0036] As discussed above, the opening and closing of the controlled power switches is selectively controlled by the power controller 108. In a recharging scheme, the power controller 108 is responsible for providing enough charge to the first and second batteries 101 and 104 so that they will remain sufficiently charged to power a connected application device or circuit. To do so, the power

controller 108 determines how much charge remains in each battery. If one of the batteries requires recharging, the power controller 108 operates to increase the charge delivered to that battery. Alternately, if a battery is sufficiently recharged, the power controller 108 operates to decrease or stop the charge being delivered to that battery.

[0037] In a recharging scheme, the power controller 108 increases the charge delivered to the first battery 101 from the external power supply 109 by increasing the amount of time that the first controlled power switch 103 is closed and decreases the charge delivered to the first battery 101 from the external power supply 109 by increasing the amount of time that the first controlled power switch 103 is open. Similarly, in a recharging scheme, the power controller 108 increases the charge delivered to the second battery 104 from the external power supply 109 by increasing the amount of time that the second controlled power switch 106 is closed and decreases the charge delivered to the second battery 104 from the external power supply 109 by increasing the amount of time that the second controlled power switch 106 is open.

[0038] As discussed above, the state of each battery 101 and 104 may be monitored on an individual basis by the power controller 108. As a result, the power controller 108 can control the rate and amount of recharging of each battery by the external supply 109 such that each battery is recharged in an optimal way. For example, the power controller 108 can operate to ensure that recharging is even applied to batteries 101 and 104.

[0039] The power supply 100 of FIG. 1 utilizes only two batteries 101 and 104. However, as will be appreciated by persons of ordinary skill in the relevant art(s) from the teachings provided herein, the discharging and recharging techniques discussed herein may be applied in a power supply with only one battery, with two batteries, or with more than two batteries. For example, the power supply 100 of FIG. 1 could be modified to include an additional battery in parallel with the first battery 101 and the second battery 104 by adding an additional inductor and

controlled power switch. The present invention includes such alternate embodiments.

[0040] FIG. 2 illustrates a high-level schematic of a battery-operated power supply circuit 200 in accordance with embodiments of the present invention. The power supply circuit 200 includes a battery 201, a shunt capacitor 202, an inductor 207, a controlled power switch 211, a load capacitor 205 and a load 206. The load 206 represents an application device or circuit to which the power supply circuit 200 is connected and for which the power supply circuit 200 provides operating power. In the embodiment shown in FIG. 2, the battery 201 is a 1.2 volt battery and the load 206 is 1.8 volts. In embodiments, the battery 201 may comprise a nickel cadmium (NiCd) battery or a nickel-metal hydride battery.

[0041] In the power supply circuit 200, the battery 201 and the inductor 207 are analogous to either the first battery 101 and the first inductor 102 or the second battery 104 and the second inductor 105 of the power supply 100 of FIG. 1. The load 206 is analogous to the load 107 of the power supply 100 of FIG. 1. Finally, the controlled power switch 211 is analogous to either of the controlled power switches 103 and 106 of the power supply 100 of FIG. 1.

[0042] In the embodiment shown in FIG. 2, the controlled power switch 211 includes a first transistor 203, a second transistor 204, a third transistor 209, a fourth transistor 212, a  $V_{\text{BOOST}}$  node 208, and a  $V_{\text{DD}}$  node 210. In embodiments, the transistors 203, 204, 209 and 212 are implemented as FETs.

[0043] The power supply 200 provides charge from the battery 201 to the load 206 via the operation of the controlled power switch 211. The operation of the controlled power switch 211 is, in turn, controlled by the application of control signal  $V_N$  to the first transistor 203 and application of control signal  $V_P$  to the second transistor 204 and the fourth transistor 212. The technique by which the control signals  $V_N$  and  $V_P$  are generated will be discussed in more detail below in regard to FIG. 3.

[0044] In the controlled power switch 211, when the control signal  $V_N$  applied to the first transistor 203 goes high, a charge  $I_L$  is permitted to build up on the

inductor 207. This is depicted, for example, in FIG. 4, which shows the control signal  $V_N$  as signal 401 and the charge  $I_L$  on the inductor 207 as signal 403. As can be seen in FIG. 4, when  $V_N$  goes high, a charge  $I_L$  builds up on the inductor 207.

[0045] When the control signal  $V_P$  applied to the second transistor 204 and the fourth transistor 212 subsequently goes high, the charge  $I_L$  on the inductor 207 is provided to the load 206. This is depicted, for example, in FIG. 4, which shows the control signal  $V_P$  as signal 402 and the charge  $I_L$  on the inductor 207 as signal 403. As can be seen in FIG. 4, when  $V_P$  goes high, the charge  $I_L$  on the inductor 207 is discharged to the load 206.

[0046] The use of third transistor 209 as opposed to a Schottky diode for controlling discharge into the load represents an improvement over conventional power supplies. This is due to the fact that the third transistor 209 may have a drain-to-source voltage that is significantly lower than the turn-on voltage of a Schottky diode. For example, the third transistor 209 may be implemented as a FET with a drain-to-source voltage of 10 mV as compared to a Schottky diode that has a typical turn-on voltage of 0.4 to 0.6 V. Because a Schottky diode has a typical turn-on voltage of about 0.4 to 0.6 volts, the use of the diode will result in an energy loss equal to the turn-on voltage times the load current. This is lost energy that could have otherwise been used by the load. Furthermore, the use of the third transistor 209 in embodiments of the present invention permits precise control of turn-off and turn-on voltages as opposed to Schottky diodes, in which the turn-on and turn-off voltages cannot be modified after manufacture.

[0047] The voltage  $V_{BOOST}$  that accumulates on node 208 indicates the current voltage level of the battery. In embodiments, the voltage at  $V_{BOOST}$  may be used to monitor the state of the battery 201 and to ensure that the battery 201 has not been completely discharged or entered into a state of reverse polarity. For example, the power controller 108 of the power supply 100 of FIG. 1 could monitor the voltage  $V_{BOOST}$ .

inductor 207. This is depicted, for example, in FIG. 4, which shows the control signal  $V_N$  as signal 401 and the charge  $I_L$  on the inductor 207 as signal 403. As can be seen in FIG. 4, when  $V_N$  goes high, a charge  $I_L$  builds up on the inductor 207.

[0045] When the control signal  $V_p$  applied to the second transistor 204 and the fourth transistor 212 subsequently goes high, the charge  $I_L$  on the inductor 207 is provided to the load 206. This is depicted, for example, in FIG. 4, which shows the control signal  $V_p$  as signal 402 and the charge  $I_L$  on the inductor 207 as signal 403. As can be seen in FIG. 4, when  $V_p$  goes high, the charge  $I_L$  on the inductor 207 is discharged to the load 206.

[0046] The use of third transistor 209 as opposed to a Schottky diode for controlling discharge into the load represents an improvement over conventional power supplies. This is due to the fact that the third transistor 209 may have a drain-to-source voltage that is significantly lower than the turn-on voltage of a Schottky diode. For example, the third transistor 209 may be implemented as a FET with a drain-to-source voltage of 10 mV as compared to a Schottky diode that has a typical turn-on voltage of 0.4 to 0.6 V. Because a Schottky diode has a typical turn-on voltage of about 0.4 to 0.6 volts, the use of the diode will result in an energy loss equal to the turn-on voltage times the load current. This is lost energy that could have otherwise been used by the load. Furthermore, the use of the third transistor 209 in embodiments of the present invention permits precise control of turn-off and turn-on voltages as opposed to Schottky diodes, in which the turn-on and turn-off voltages cannot be modified after manufacture.

[0047] The voltage  $V_{BOOST}$  that accumulates on node 208 indicates the current voltage level of the battery. In embodiments, the voltage at  $V_{BOOST}$  may be used to monitor the state of the battery 201 and to ensure that the battery 201 has not been completely discharged or entered into a state of reverse polarity. For example, the power controller 108 of the power supply 100 of FIG. 1 could monitor the voltage  $V_{BOOST}$ .

[0048] The voltage  $V_{DD}$  that appears at node 210 of power supply circuit 200 indicates the voltage across the load 206 (the "load voltage").

[0049] In the power supply circuit 200, the shunt capacitor 202 is provided in parallel with the battery 201 to act as a shunt in case there is any inductive "back-kick" onto the battery, as will be understood by those skilled in the art. Additionally, the load capacitor 205 is provided in parallel with the load 206 to act as a charge buffer in the instance of sudden load changes. As is further discussed herein, embodiments of the present invention permit the use of a very small load capacitor (e.g., 10  $\mu$ F) as compared to the load capacitors used in conventional power supply circuits.

[0050] The power supply circuit 200 of FIG. 2 is shown using only one battery 201. However, as will be appreciated by persons of ordinary skill in the relevant art(s) from the teachings provided herein, the power supply circuit 200 of FIG. 2 could be modified to use two or more batteries. For example, this could be achieved by connecting an identical configuration of shunt capacitor 202, inductor 207, controlled power switch 211, and load capacitor 205 in parallel to the load 206 for each battery to be added.

[0051] FIG. 3 is a functional block diagram of a power control circuit 300 that comprises a part of a power controller used in a power supply in accordance with an embodiment of the present invention. The power control circuit 300 monitors the load voltage and controls the operation of a controlled power switch in power supply circuit embodiments of the present invention. For example, the power control circuit 300 may be used to control the operation of the controlled power switch 211 in the power supply circuit 200 of FIG. 2. Also, in an embodiment, the power control circuit 300 of FIG. 3 may comprise part of the power controller 108 of FIG. 1.

[0052] The power control circuit 300 includes a clock 301, a comparator 302, a digital control module 303, a  $V_p$  counter 306, and a  $V_N$  counter 307. In an embodiment, the components of the power control circuit 300 are entirely

implemented as digital components. For example, the components of the power control circuit 300 may be implemented in digital CMOS.

[0053] The comparator 302 is used by the power control circuit 300 to determine if the voltage across the load,  $V_{DD}$ , is sufficient to power the attached application circuit or device. In the power control circuit 300, the comparator makes this determination by comparing  $V_{DD}/2$  to a reference voltage,  $V_{REF}$ , that is equal to the desired operating voltage divided by 2. The input  $V_{DD}/2$  may be generated by running the output voltage  $V_{DD}$  through a simple resistor divider network or a capacitor divider network. The reference voltage  $V_{REF}$  may be obtained by a bandgap reference circuit or other circuit known to persons skilled in the art for generating reference voltages. As an example, in the power supply circuit 200 of FIG. 2, the desired operating voltage is 1.8 volts. Therefore, an appropriate value for  $V_{REF}$  would be 0.9 volts.

[0054] By comparing the load voltage  $V_{DD}$  to the reference voltage  $V_{REF}$ , the comparator 302 provides an indication to the digital control module 303 of whether the load voltage  $V_{DD}$  is above or below the desired level. In response, the digital control module 303 uses this information to generate control signals  $V_P$  and  $V_N$  in a manner that will either increase or decrease the amount of charge delivered to the load in order to achieve the desired voltage level.

[0055] As will be appreciated by persons skilled in the art, a wide variety of comparators 302 may be used to monitor the level of the load voltage  $V_{DD}$ . Additionally, more than one comparator may be used. For example, in an embodiment, one window comparator could be used to determine if  $V_{DD}$  is very close to the desired level, so that only minor modifications to the control signals  $V_P$  and  $V_N$  need be made, while an additional two comparators could be used to determine if  $V_{DD}$  is much further away from the desired level, such that greater modifications to the control signals  $V_P$  and  $V_N$  need be made.

[0056] In a further embodiment, the clock 301 is used to provide timing information to the digital control module 303, and a determination is made as to how long the load voltage  $V_{DD}$  has been above or below the desired supply level.

The digital control module 303 then modifies the controls signals  $V_p$  and  $V_N$  accordingly, so that the load voltage  $V_{DD}$  will be increased or decreased in greater proportion depending on how long  $V_{DD}$  has been away from the desired supply.

[0057] The digital control module 303 generates the control signals  $V_p$  and  $V_N$  that control the operation of a controlled power switch in a power supply in accordance with embodiments of the present invention. For example, the digital control module 303 may generate the control signals  $V_p$  and  $V_N$  that control the operation of the controlled power switch 211 in the power supply 200 of FIG. 2.

[0058] In an embodiment, the control signals  $V_p$  and  $V_N$  each comprise a series of pulses of a fixed pulse width and the digital control module 303 controls the frequency of the pulses for each signal. In other words, the digital control module 303 controls the number of intervals between pulses in the signals  $V_p$  and  $V_N$ . By increasing the frequency of the pulses, the digital control module 303 can increase the amount of time that the controlled power switch discharges the battery into the load. Alternately, by decreasing the frequency of the pulses, the digital control module 303 can decrease the amount of time that the controlled power switch discharges the battery into the load. For example, in order to pull charge out of the battery only 50% of the time, the digital control module 303 will generate  $V_p$  and  $V_N$  signals in which every pulse is followed by a time off equal to the pulse width. As a further example, if only 25% discharging is required, the digital control module 303 will generate  $V_p$  and  $V_N$  signals in which every pulse is followed by a time off equal to three pulse widths.

[0059] In order to generate the control signals  $V_p$  and  $V_N$  at a fixed frequency the digital control module 303 uses the clock 301 as a reference. In embodiments, the clock 301 operates at 12 MHz. In a further embodiment, the digital control module 303 generates the control signals  $V_p$  and  $V_N$  at the same frequency in order to avoid creating harmonics in the power supply circuit that may interfere with a connected application device or circuit.

[0060] Persons skilled in the relevant art will appreciate that the digital control module 303 may implement other algorithms for generating the control signals  $V_p$



and  $V_N$  in order to increase or decrease the amount of time that the controlled power switch discharges the battery into the load. For example, in an alternate embodiment, the digital control module 303 can alter the pulse width of the control signals  $V_P$  and  $V_N$  in order to increase or decrease the amount of time that the controlled power switch discharges the battery into the load. The present invention is directed to such other algorithms.

[0061] In an embodiment, the power control circuit 300 is implemented on the same chip as the application circuit energized by the power supply. For example, the power control circuit 300 may be implemented along with the application circuit in digital CMOS. In an implementation of this type, the application circuit may provide the digital control module 303 with *a priori* information about an impending load change. For example, the application circuit may provide the digital control module 303 with information about an impending increase or decrease in the load. When the digital control module 303 receives this advanced information about the application circuit, it can adjust the control signals  $V_P$  and  $V_N$  accordingly to increase or decrease the output voltage  $V_{DD}$ . Because the digital control module can receive advance information about load changes from the application circuit, a power supply using the power controller does not require a large capacitor in parallel with the load to act as a charge buffer for dealing with sudden load changes.

[0062] In the power control circuit 300, the  $V_P$  counter 306 accumulates information about the control signal  $V_P$ , including how long  $V_P$  has been turned on. Similarly, the  $V_N$  counter 307 accumulates information about the control signal  $V_N$ , including how long  $V_N$  has been turned on. The counters 306 and 307 scale this information with appropriate scaling factors (such as factors relating to the size of the inductor and load capacitor attached to the controlled power switch controlled by the control signals  $V_N$  and  $V_P$ ) to determine precisely how much charge has been removed from the battery whose discharge is controlled by the control signals  $V_N$  and  $V_P$ .

[0063] The counters 308 and 309 can thus report the status of the battery to the user via an LED or other display. For example, the counters 308 and 309 may provide a warning to the user when a battery's charge is low or when a battery is depleted. In an alternate embodiment, the counters 308 and 309 provide information about the status of the battery to the digital controller 303, which can use the information to determine whether to modify the control signals  $V_N$  and  $V_P$ . For example, in an instance where the counters 308 and 309 determine that the battery is close to depletion or has been completely discharged, the digital control module 303 can turn off  $V_N$  and  $V_P$  to ensure that no more charge is removed from the battery.

[0064] In embodiments, the counter 306 and 307 are implemented as simple digital counters controlled by the clock 301.

[0065] It will be appreciated by persons of ordinary skill in the art from the teachings provided herein that the power control circuit 300 of FIG. 3 may also be used to implement a battery recharging scheme. In recharging embodiments of the present invention, the power control circuit 300 is used to monitor the state of a battery (as opposed to monitoring a load voltage) and to generate control signals  $V_N$  and  $V_P$  to control the amount and rate of charge provided to the battery (as opposed to the load). The invention is directed to such recharging schemes.

[0066] In an embodiment, a system using a battery-operated power supply of the type described herein can provide new and useful configurations for products. For example, a system such as a headset can be built in modules. The headset could comprise two pieces: a basic monaural version (single headphone) with the electronics and a battery built in, and a second headphone for stereo use. If a user wants to use the headset as a stereo headset, he can attach the second headphone, which has its own battery. Stereo mode would require more power and the second headphone would provide that power. Configuring the power supply to operate off of any number of cells or batteries in parallel, as described herein, provides a new level of flexibility in product design and configuration, which is

difficult to do with batteries running in series. A system can be made in modules, each with its own battery, which can be placed in parallel with the batteries in other modules. A power controller, such as the power controller 108 described in reference to FIG. 1, can then provide balancing of the available power from the plurality of batteries to match the plurality of loads.

[0067] While specific embodiments of the present invention have been described above, it should be understood that they have been presented by way of example only, and not limitation. It will be understood by those skilled in the art that various changes in form and details may be made therein without departing from the spirit and scope of the invention as defined in the appended claims. Thus, the breadth and scope of the present invention should not be limited by any of the above-described exemplary embodiments, but should be defined only in accordance with the following claims and their equivalents.

100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000 1001 1002 1003 1004 1005 1006 1007 1008 1009 1010 1011 1012 1013 1014 1015 1016 1017 1018 1019 1020 1021 1022 1023 1024 1025 1026 1027 1028 1029 1030 1031 1032 1033 1034 1035 1036 1037 1038 1039 1040 1041 1042 1043 1044 1045 1046 1047 1048 1049 1050 1051 1052 1053 1054 1055 1056 1057 1058 1059 1060 1061 1062 1063 1064 1065 1066 1067 1068 1069 1070 1071 1072 1073 1074 1075 1076 1077 1078 1079 1080 1081 1082 1083 1084 1085 1086 1087 1088 1089 1090 1091 1092 1093 1094 1095 1096 1097 1098 1099 1100 1101 1102 1103 1104 1105 1106 1107 1108 1109 1110 1111 1112 1113 1114 1115 1116 1117 1118 1119 1120 1121 1122 1123 1124 1125 1126 1127 1128 1129 1130 1131 1132 1133 1134 1135 1136 1137 1138 1139 1140 1141 1142 1143 1144 1145 1146 1147 1148 1149 1150 1151 1152 1153 1154 1155 1156 1157 1158 1159 1160 1161 1162 1163 1164 1165 1166 1167 1168 1169 1170 1171 1172 1173 1174 1175 1176 1177 1178 1179 1180 1181 1182 1183 1184 1185 1186 1187 1188 1189 1190 1191 1192 1193 1194 1195 1196 1197 1198 1199 1200 1201 1202 1203 1204 1205 1206 1207 1208 1209 1210 1211 1212 1213 1214 1215 1216 1217 1218 1219 1220 1221 1222 1223 1224 1225 1226 1227 1228 1229 1230 1231 1232 1233 1234 1235 1236 1237 1238 1239 1240 1241 1242 1243 1244 1245 1246 1247 1248 1249 1250 1251 1252 1253 1254 1255 1256 1257 1258 1259 1260 1261 1262 1263 1264 1265 1266 1267 1268 1269 1270 1271 1272 1273 1274 1275 1276 1277 1278 1279 1280 1281 1282 1283 1284 1285 1286 1287 1288 1289 1290 1291 1292 1293 1294 1295 1296 1297 1298 1299 1300 1301 1302 1303 1304 1305 1306 1307 1308 1309 1310 1311 1312 1313 1314 1315 1316 1317 1318 1319 1320 1321 1322 1323 1324 1325 1326 1327 1328 1329 1330 1331 1332 1333 1334 1335 1336 1337 1338 1339 1340 1341 1342 1343 1344 1345 1346 1347 1348 1349 1350 1351 1352 1353 1354 1355 1356 1357 1358 1359 1360 1361 1362 1363 1364 1365 1366 1367 1368 1369 1370 1371 1372 1373 1374 1375 1376 1377 1378 1379 1380 1381 1382 1383 1384 1385 1386 1387 1388 1389 1390 1391 1392 1393 1394 1395 1396 1397 1398 1399 1400 1401 1402 1403 1404 1405 1406 1407 1408 1409 1410 1411 1412 1413 1414 1415 1416 1417 1418 1419 1420 1421 1422 1423 1424 1425 1426 1427 1428 1429 1430 1431 1432 1433 1434 1435 1436 1437 1438 1439 1440 1441 1442 1443 1444 1445 1446 1447 1448 1449 1450 1451 1452 1453 1454 1455 1456 1457 1458 1459 1460 1461 1462 1463 1464 1465 1466 1467 1468 1469 1470 1471 1472 1473 1474 1475 1476 1477 1478 1479 1480 1481 1482 1483 1484 1485 1486 1487 1488 1489 1490 1491 1492 1493 1494 1495 1496 1497 1498 1499 1500 1501 1502 1503 1504 1505 1506 1507 1508 1509 1510 1511 1512 1513 1514 1515 1516 1517 1518 1519 1520 1521 1522 1523 1524 1525 1526 1527 1528 1529 1530 1531 1532 1533 1534 1535 1536 1537 1538 1539 1540 1541 1542 1543 1544 1545 1546 1547 1548 1549 1550 1551 1552 1553 1554 1555 1556 1557 1558 1559 1560 1561 1562 1563 1564 1565 1566 1567 1568 1569 1570 1571 1572 1573 1574 1575 1576 1577 1578 1579 1580 1581 1582 1583 1584 1585 1586 1587 1588 1589 1590 1591 1592 1593 1594 1595 1596 1597 1598 1599 1600 1601 1602 1603 1604 1605 1606 1607 1608 1609 1610 1611 1612 1613 1614 1615 1616 1617 1618 1619 1620 1621 1622 1623 1624 1625 1626 1627 1628 1629 1630 1631 1632 1633 1634 1635 1636 1637 1638 1639 1640 1641 1642 1643 1644 1645 1646 1647 1648 1649 1650 1651 1652 1653 1654 1655 1656 1657 1658 1659 1660 1661 1662 1663 1664 1665 1666 1667 1668 1669 1670 1671 1672 1673 1674 1675 1676 1677 1678 1679 1680 1681 1682 1683 1684 1685 1686 1687 1688 1689 1690 1691 1692 1693 1694 1695 1696 1697 1698 1699 1700 1701 1702 1703 1704 1705 1706 1707 1708 1709 1710 1711 1712 1713 1714 1715 1716 1717 1718 1719 1720 1721 1722 1723 1724 1725 1726 1727 1728 1729 1730 1731 1732 1733 1734 1735 1736 1737 1738 1739 1740 1741 1742 1743 1744 1745 1746 1747 1748 1749 1750 1751 1752 1753 1754 1755 1756 1757 1758 1759 1760 1761 1762 1763 1764 1765 1766 1767 1768 1769 1770 1771 1772 1773 1774 1775 1776 1777 1778 1779 1780 1781 1782 1783 1784 1785 1786 1787 1788 1789 1790 1791 1792 1793 1794 1795 1796 1797 1798 1799 1800 1801 1802 1803 1804 1805 1806 1807 1808 1809 1810 1811 1812 1813 1814 1815 1816 1817 1818 1819 1820 1821 1822 1823 1824 1825 1826 1827 1828 1829 1830 1831 1832 1833 1834 1835 1836 1837 1838 1839 1840 1841 1842 1843 1844 1845 1846 1847 1848 1849 1850 1851 1852 1853 1854 1855 1856 1857 1858 1859 1860 1861 1862 1863 1864 1865 1866 1867 1868 1869 1870 1871 1872 1873 1874 1875 1876 1877 1878 1879 1880 1881 1882 1883 1884 1885 1886 1887 1888 1889 1890 1891 1892 1893 1894 1895 1896 1897 1898 1899 1900 1901 1902 1903 1904 1905 1906 1907 1908 1909 1910 1911 1912 1913 1914 1915 1916 1917 1918 1919 1920 1921 1922 1923 1924 1925 1926 1927 1928 1929 1930 1931 1932 1933 1934 1935 1936 1937 1938 1939 1940 1941 1942 1943 1944 1945 1946 1947 1948 1949 1950 1951 1952 1953 1954 1955 1956 1957 1958 1959 1960 1961 1962 1963 1964 1965 1966 1967 1968 1969 1970 1971 1972 1973 1974 1975 1976 1977 1978 1979 1980 1981 1982 1983 1984 1985 1986 1987 1988 1989 1990 1991 1992 1993 1994 1995 1996 1997 1998 1999 2000 2001 2002 2003 2004 2005 2006 2007 2008 2009 2010 2011 2012 2013 2014 2015 2016 2017 2018 2019 2020 2021 2022 2023 2024 2025 2026 2027 2028 2029 2030 2031 2032 2033 2034 2035 2036 2037 2038 2039 2040 2041 2042 2043 2044 2045 2046 2047 2048 2049 2050 2051 2052 2053 2054 2055 2056 2057 2058 2059 2060 2061 2062 2063 2064 2065 2066 2067 2068 2069 2070 2071 2072 2073 2074 2075 2076 2077 2078 2079 2080 2081 2082 2083 2084 2085 2086 2087 2088 2089 2090 2091 2092 2093 2094 2095 2096 2097 2098 2099 2100 2101 2102 2103 2104 2105 2106 2107 2108 2109 2110 2111 2112 2113 2114 2115 2116 2117 2118 2119 2120 2121 2122 2123 2124 2125 2126 2127 2128 2129 2130 2131 2132 2133 2134 2135 2136 2137 2138 2139 2140 2141 2142 2143 2144 2145 2146 2147 2148 2149 2150 2151 2152 2153 2154 2155 2156 2157 2158 2159 2160 2161 2162 2163 2164 2165 2166 2167 2168 2169 2170 2171 2172 2173 2174 2175 2176 2177 2178 2179 2180 2181 2182 2183 2184 2185 2186 2187 2188 2189 2190 2191 2192 2193 2194 2195 2196 2197 2198 2199 2200 2201 2202 2203 2204 2205 2206 2207 2208 2209 2210 2211 2212 2213 2214 2215 2216 2217 2218 2219 2220 2221 2222 2223 2224 2225 2226 2227 2228 2229 2230 2231 2232 2233 2234 2235 2236 2237 2238 2239 2240 2241 2242 2243 2244 2245 2246 2247 2248 2249 2250 2251 2252 2253 2254 2255 2256 2257 2258 2259 2260 2261 2262 2263 2264 2265 2266 2267 2268 2269 2270 2271 2272 2273 2274 2275 2276 2277 2278 2279 2280 2281 2282 2283 2284 2285 2286 2287 2288 2289 2290 2291 2292 2293 2294 2295 2296 2297 2298 2299 2300 2301 2302 2303 2304 2305 2306 2307 2308 2309 2310 2311 2312 2313 2314 2315 2316 2317 2318 2319 2320 2321 2322 2323 2324 2325 2326 2327 2328 2329 2330 2331 2332 2333 2334 2335 2336 2337 2338 2339 2340 2341 2342 2343 2344 2345 2346 2347 2348 2349 2350 2351 2352 2353 2354 2355 2356 2357 2358 2359 2360 2361 2362 2363 2364 2365 2366 2367 2368 2369 2370 2371 2372 2373 2374 2375 2376 2377 2378 2379 2380 2381 2382 2383 2384 2385 2386 2387 2388 2389 2390 2391 2392 2393 2394 2395 2396 2397 2398 2399 2400 2401 2402 2403 2404 2405 2406 2407 2408 2409 2410 2411 2412 2413 2414 2415 2416 2417 2418 2419 2420 2421 2422 2423 2424 2425 2426 2427 2428 2429 2430 2431 2432 2433 2434 2435 2436 2437 2438 2439 2440 2441 2442 2443 2444 2445 2446 2447 2448 2449 2450 2451 2452 2453 2454 2455 2456 2457 2458 2459 2460 2461 2462 2463 2464 2465 2466 2467 2468 2469 2470 2471 2472 2473 2474 2475 2476 2477 2478 2479 2480 2481 2482 2483 2484 2485 2486 2487 2488 2489 2490 2491 2492 2493 2494 2495 2496 2497 2498 2499 2500 2501 2502 2503 2504 2505 2506 2507 2508 2509 2510 2511 2512 2513 2514 2515 2516 2517 2518 2519 2520 2521 2522 2523 2524 2525 2526 2527 2528 2529 2530 2531 2532 2533 2534 2535 2536 2537 2538 2539 2540 2541 2542 2543 2544 2545 2546 2547 2548 2549 2550 2551 2552 2553 2554 2555 2556 2557 2558 2559 2560 2561 2562 2563 2564 2565 2566 2567 2568 2569 2570 2571 2572 2573 2574 2575 2576 2577 2578 2579 2580 2581 2582 2583 2584 2585 2586 2587 2588 2589 2590 2591 2592 2593 2594 2595 2596 2597 2598 2599 2600 2601 2602 2603 2604 2605 2606 2607 2608 2609 2610 2611 2612 2613 2614 2615 2616 2617 2618 2619 2620 2621 2622 2623 2624 2625 2626 2627 2628 2629 2630 2631 2632 2633 2634 2635 2636 2637 2638 2639 2640 2641 2642 2643 2644 2645 2646 2647 2648 2649 2650 2651 2652 2653 2654 2655 2656 2657 2658 2659 2660 2661 2662 2663 2664 2665 2666 2667 2668 2669 2670 2671 2672 2673 2674 2675 2676 2677 2678 2679 2680 2681 2682 2683 2684 2685 2686 2687 2688 2689 2690 2691 2692 269